

# DUAL DC POWER SUPPLY

## ■ Low noise level power supply unit

This low noise type power supply unit has high reliability, low temperature coefficient, quick responding transient characteristics and excellent regulation.

## ■ Easy setting of voltage

Two potentiometers make it easy to fine tune the voltage setting.

## ■ Use as constant current power supply

This power supply may be converted to a stable constant current power supply. Current value may be set continuously or variable with potentiometer.



## SPECIFICATIONS

## Raptec-3002

|                                  |   |
|----------------------------------|---|
| DC Output voltage adjust         | DUAL 0 - 30V  |
| DC Output current adjust         | DUAL 0 - 2A   |
| Loading regulation               | 0.5% $\pm$ 5 mV                                     |
| Line Regulation                  | 0.5% $\pm$ 5 mV                                     |
| Ripple and noise                 | 6 mV(RMS)   |
| Output voltage & current monitor | 4 Analog meter                                      |
| Protection                       | Automatic reset overload & short circuit protection |
| Power source                     | 220VAC  |
| Dimensions (approx.)             | 255(W) x 150(H) x 340(D) mm.                        |

\*Specifications are subject to change without notice.